

		1		2		3		4		5		6		7		8	
A	电机规格													序号		型号	
	额定功率(W)		4000											1		DXM-L130C-40030-3C2-A1	
	额定电压(V)		380											2		DXM-L130A-40030-3C2-A1	
	额定转矩(Nm)		12.6														
	最大转矩(Nm)		37.8														
	额定电流(Arms)		12.96														
	最大电流(Arms)		37.1														
	额定转速(rpm)		3000														
B	最大转速(rpm)		6000														
	频率(Hz)		250														
	转动惯量($\times 10^{-4}\text{kg}\cdot\text{m}^2$)		11.04														
	线电阻(Ω)		$0.298\pm 5\%$														
	线电感Q (mH)		$4.85\pm 20\%$														
	线电感D (mH)		$4.7\pm 20\%$														
	线反电势(V/1000rpm)		$67.87\pm 8\%$														
	转矩常数 (Nm/Arms)		0.972														
	电气时间常数 (ms)		16.032														
	C	极对数		5													
重量 (kg)		14.7															
单体包装重量 (kg)		15.7															
集合包装数量 (Pcs)		N/A															
集合包装重量 (kg)		N/A															
制动器 (保持型)																	
制动器额定电压 (V)		DC24															
制动器保持扭矩 (Nm)		16															
制动器额定功率 (W)		24															
制动器额定电阻 (Ω)		$24\pm 7\%$															
D																	
零件代号																	
借(通)用件登记																	
描图																	
描校																	
旧底图总号																	
底图总号																	
签字																	
日期																	
1		2		3		4		5		6		7		8			
1		2		3		4		5		6		7		8			
1		2		3		4		5		6		7		8			
1		2		3		4		5		6		7		8			
1		2		3		4		5		6		7		8			
1		2		3		4		5		6		7		8			
1		2		3		4		5		6		7		8			
1		2		3		4		5		6		7		8			
1		2		3		4		5		6		7		8			
1		2		3		4		5		6		7		8			
1		2		3		4		5		6		7		8			
1		2		3		4		5		6		7		8			
1		2		3		4		5		6		7		8			
1		2		3		4		5		6		7		8			
1		2		3		4		5		6		7		8			
1		2		3		4		5		6		7		8			
1		2		3		4		5		6		7		8			
1		2		3		4		5		6		7		8			
1		2		3		4		5		6		7		8			
1		2		3		4		5		6		7		8			
1		2		3		4		5		6		7		8			
1		2		3		4		5		6		7		8			
1		2		3		4		5		6		7		8			
1		2		3		4		5		6		7		8			
1		2		3		4		5		6		7		8			
1		2		3		4		5		6		7		8			
1		2		3		4		5		6		7		8			
1		2		3		4		5		6		7		8			
1		2		3		4		5		6		7		8			
1		2		3		4		5		6		7		8			
1		2		3		4		5		6		7		8			
1		2		3		4		5		6		7		8			
1		2		3		4		5		6		7		8			
1		2		3		4		5		6		7		8			
1		2		3		4		5		6		7		8			
1		2		3		4		5		6		7		8			
1		2		3		4		5		6		7		8			
1		2		3		4		5		6		7		8			
1		2		3		4		5		6		7		8			
1		2		3		4		5		6		7		8			
1		2		3		4		5		6		7		8			
1		2		3		4		5		6		7		8			